

## Garmin GTR 225 Version 1 - Summary of Features

Two GTR 225 radios are provided, COM1 and COM2:

GTR 225 COM1, filename: **GarminCom!GTR225\_JD\_1**

GTR 225 COM2, filename: **GarminCom!GTR225\_JD\_2**



### Features

#### General

- Comprehensive and accurate simulation of real GTR 225 COM radio.
- Knobs can be pushed-in using middle click (click mouse wheel).
- Full documentation (Pilot's Guide) provided.

#### COM Radio

- Standby Frequency set by clicking knobs, or by using mouse-wheel.
- Flip-flop (↔) button to swap frequencies.
- Automatic ID (ICAO) and type display.
- Push the kHz tune knob for 50 kHz step feature (frequency can be set in 25 kHz or 50 kHz steps).
- Functional On/Off switch.
- Push COM volume knob for PUSH SQ feature (squelch off – can hear background hiss).
- COM Frequency Save/Recall Mode:
  - Fifteen programmable non-volatile channels are provided.
  - Select required channel by clicking kHz tune knob, or by using mouse-wheel.
  - Press the FUNC button to access the SAVE/RECALL menu.

#### Timers

- Two independent timers are provided:
  - Up Timer.
  - Down Timer.

#### Menu System

- A simplified sub-set of the real GTR225 menu system is provided.